

# DIVA HD

## DVB-T2, HEVC H.265 Receiver

### freenet TV compliant

freenet TV



- HEVC H.265 (Full HD).
- DVB-T/DVB-T2.
- freenet TV reception.
- Multimedia player.
- 4 digits green LED display.

#### • SINGLE TUNER DVB-T2 FULL HD RECEIVER WITH SECURED CAS EMBEDDED

- HEVC H.265 embedded to receive Full HD programs. Receiver also compliant with MPEG2 and MPEG4 HD (H.264) standards.
- DVB-T2 HD receiver, ready for the Switch Off.
- Irdeto embedded to receive freenet TV package.

#### • MULTIMEDIA PLAYER VIA USB

- Multimedia player for photos, videos and music from external hard drive.

#### • EASE OF USE

- Plug & Play receiver.
- Favourite lists.
- Electronic Program Guide (7 days), parental control, timer...

#### • DESIGN

- Ultra compact design.
- 4 digits green LED display.
- 3 switches: ON/OFF, CH-, CH+.



Powered by **aston**<sup>®</sup>

## ● TECHNICAL FEATURES

- Single tuner.
- Irdeto embedded.
- 1 smart card reader.
- Dolby Digital Audio.
- Transmission standards: DVB-T/DVB-T2.
- Video decoding: MPEG2, MPEG4 HD (H.264), HEVC (H.265) Full HD.
- Output resolution: 1080p/1080i/720p/576p/576i/480p/480i (HDMI)/576i:480i (CVBS).
- Audio decoder: MPEG-1-2, MP3, AAC-LC, WMA, HE-AAC 5.1.
- Screen ratio: 16:9 and 4:3.
- Channel Frequency: VHF (174~230 MHz), UHF (470~806MHz).
- Operating temperature: +5 to +40°C.
- Power on consumption: <6 W.
- Standby consumption: <0,5 W.
- Power voltage: input AC 100-240V 50/60 Hz, output 12V DC.

## ● CONNECTORS

- 1 antenna input ANT IN.
- 1 antenna output ANT OUT.
- 1 Ethernet port (RJ45).
- 1 USB port 2.0.
- 1 HDMI output.
- 1 Coaxial audio output.
- 1 SCART output (TV).
- Power connector.

## ● BOX CONTENT

- DIVA HD, DVB-T2 HD HEVC receiver.
- Remote control + AAA batteries.
- Power supply.
- Quick starter guide.



Non contractual pictures.

## CONTACT

**Frédéric LESELLIER**

Sales Area Manager

[frederic.lesellier@aston-france.com](mailto:frederic.lesellier@aston-france.com)

Powered by **aston**<sup>®</sup>